

# 6500-15KW

## Rotary Phase Converter Data Sheet



**TEMCo** Heavy Duty Rotary Phase Converters provide utility quality three phase power from a single phase power supply. TEMCo's world class products are being used throughout the United States and internationally.

### Common Phase Converter Uses:


- Machine Shops
- Woodworking
- Farm Equipment
- Restaurant Equipment
- Petrochemicals
- Home Hobbyist
- Oil Fields
- Irrigation
- High Tech
- Military
- Aerospace
- Hospitals




### Phase Converter Features:


**6yr** Full 6 Year Warranty

**HEAVY DUTY** Rugged Heavy Duty Rotary Design

 100% Copper Windings  
(Energy Efficient, Environmentally Friendly)

 100% American Made

 208-240v or 440-480v Operation

 Quiet Operation, 63db @ 10ft  
(No Louder Than Human Conversation)

### Specifications:

1-Phase Input Voltage	208-240v or 440-480v	
1-Phase Input Frequency	60 Hz	
3-Phase Output Voltage	= 1-Phase Volts + 5% on L2 (Non-Loaded)	
3-Phase Output Frequency	60 Hz	
3-Phase Output Voltage Balance	± 5%	
3-Phase Output Phase Angle	120°	
Temperature Rating	40° C Ambient Continuous	
Ambient Humidity	<95% (Non-Condensing)	
Maximum Altitude	3,300 ft. Above Sea Level (De-rate 20% if above 3,300 ft.)	
Enclosure	NEMA 1 (Indoor)	
	<b>230v</b>	<b>460v</b>
Maximum <b>Medium</b> Run or Start HP	10 HP	10 HP
Maximum <b>Hard</b> Run or Start HP	6.6 HP	6.6 HP
Maximum Group Load HP	13.3 HP	13.3 HP
Continuous 3-Phase Output Amps	37.5 Amps	18.75 Amps
Peak 3-Phase Output Amps	50 Amps	25 Amps
Peak kW Output	15 kW	15 kW
Peak 1-Phase Amps Required	86 Amps	43 Amps
Approximate 1-Phase Idle Amps	7 Amps	3.5 Amps
1-Phase Breaker Recommended	100 Amps	50 Amps
1-Phase Fuse Recommended	90 Amp Dual-Element Time Delay	45 Amp Dual-Element Time Delay
Recommended 1-Phase Wire Size	3 AWG	8 AWG
Recommended 3-Phase Wire Size	6 AWG	10 AWG

TEMCo – Tower Electric Motor Co.  
41474 Christy St. Fremont, CA 94538

Inside USA (800) 613-2290 International (510) 490-2187  
www.temcophaseconverter.com Fax (510) 490-1507